



BMC

BASS MID CONTROL

The new Bass Mid Control is the active mid-controller for bass players. A small but powerful pedal that provides frequency control adjustments between 120Hz ~ 3kHz. When using 2-band EQ or passive bass, the Frequency control provides excellent manipulation of the mid frequencies, while the Boost/Cut gives you boosting or cutting capabilities of up to + / - 12dB. This compact pedal can also be powered by a 9V battery or for additional headroom use an 18V power adapter. This pedal will provide you the flexibility to play any musical style.

Boost/Cut

You can adjust the amount of boost/cut of mid frequency +/-12dB

The Boost/Cut knob may turn slightly when the Frequency knob is turned quickly. This does not mean the product is defective.

Frequency

You can set the range of the mid frequency EQ
Range is between 120Hz~3KHz

- 7 o'clock : 120Hz
- 9 o'clock : 160Hz
- 11 o'clock : 500Hz
- 12 o'clock : 630Hz
- 1 o'clock : 800Hz
- 3 o'clock : 2KHz
- 5 o'clock : 3KHz

Spec

- Size(W/D/H) 90mm/50mm/70mm
- Weight 320g
- True Bypass Switching
- Power Consumption 9VDC/3.3mA
(*18VDC- only with DC adapter jack.
18VDC/6.6mA)
- Batter Type 9VDC(006P)x1
- AC Adapter (Optional) 9 ~ 18VDC, Negative Tips
(Regulated recommended such as Dunlop ECB04 Power Supply)



Recommended Settings



Frequency at 10 o'clock and Boost/Cut at 4 o'clock for fretless virtuoso sound.



Frequency at 1 o'clock, Boost/Cut at 9 o'clock and internal Trimmer slightly boosted for great slap sound.

Internal Trimmer



Output Level: Factory setting is no volume difference compared to Bypass. You can adjust this with the internal Trimmer depending on the equipment you use.

www.ews-us.com

distributed by Prosound Communications Inc.

www.prosoundcommunications.com